

The **SEELEVEL II™** Tank Monitor



P Version



LT Version



FF Version



TT Version

Features

- Full featured system designed specifically for OEM's
- Provides accurate tank level information using percentage of full readout
- Fresh, grey and black water tanks are monitored using Garnet's proprietary external level sensing technology. This ends fouling problems caused by debris build-up in the holding tank. Detailed diagnostic information monitors sender operation.
- Measures tanks up to 17 inches tall with a single sender or 33 inches tall with dual senders
- LPG tank connection compatible with existing electric senders
- LPG auto calibrates at first fill of tank
- Multiple versions meet the needs of differing configurations:
 - P: Three holding tanks, LPG tank, inside temp., water pump switch
 - LT: Three holding tanks, LPG tank, inside temp., water pump/heater switches
 - FF: Four holding tanks, LPG tank
 - TT: Three holding tanks, LPG tank, inside and outside temperature
- Uses common industry connector for ease of installation and servicing

IT'S THE 21st CENTURY...WELCOME TO IT!

 **GARNET**
TECHNOLOGIES INC.

Your Dealer:

AA Solar & Sun Power Plus

34A Forge Road, Silverdale, Auckland 0932

Ph/Fax: 09 427 4040 Ph: 09 427 4143 Mob: 027 490 5901

www.aasolar.co.nz www.sunpowerplus.co.nz

sales@aasolar.co.nz sales@sunpowerplus.co.nz

MODEL 712 *SEELVEL II*[™] TANK MONITOR SPECIFICATIONS

Resolution:	1/4 inch (6 mm)
Accuracy:	+/- 5% or better, limited by resolution and tank shape
Operating temperature range:	+32 to +140 °F (0 to + 60°C)
Sender materials:	0.008" thick glass epoxy circuit board with conformal coating for circuit protection. Laminated on the back with 3M 300LSE Bonding Adhesive.
Display mounting panel:	Black panel, approximately 6 3/4" wide by 3 3/4" high by 1" thick (146mm wide X 95mm high X 25mm deep). Panel screws to wall. Required cutout size is 5 3/4" wide by 2 3/4" high.
System power requirements:	Display requires 12 volts from the RV battery, the system will function from 11 volts to 16 volts. Current drain is less than 200mA.
Wiring:	Two wire conductor required from the display to each sender. 12 V power and ground required for display. Single wire required for LPG sender if sender grounded at tank.
LPG sender characteristics:	Display will work with an LPG sender maximum resistance of 50 ohms to 500 ohms. Display shows increasing level as resistance increases. System must be calibrated with the LP tank full.